

VIVALDI

 Datasheet

Vivaldi MULTIMEDIA P40SL



Multimedia class-D stereo power amplifier with integrated Keysol WiFi player.

40+40W @ 80hm, 70+70W @ 40hm.

VIVALDI supervision and control APP (downloadable from iOS & Android).

1 LINE INPUT.

1 TOSLINK DIGITAL INPUT and RCA.

1 BALANCED STEREO OUTPUT for power expansions ([Vivaldi Giove A25SBTC](#), [Vivaldi MULTIMEDIA E30S](#), [Vivaldi MULTIMEDIA E80S](#), 8Ω/100V Vivaldi Ulisse Line power amps) or active subwoofers.

1 RJ45 per LAN.

1x 1m PATCH cable.

Audio parameter control with volume/settings from App.

Power supply 24Vdc via [Vivaldi Giove AL5B](#) (not included).

DIN standard (6 modules).

Size (WxHxD): 108x90x63 mm.

Weight 0.25 Kg.

Vivaldi srl ongoing effort to improve its products, reserves the right to make technical and aesthetic changes effectively without obligation to notice

 Images

Vivaldi MULTIMEDIA P40SL

Vivaldi srl

Via E. Fermi, 8 Z.I. EST - 30020 Noventa di Piave (Venezia) ITALIA
Tel. +39 0421 307825 - info@vivaldigroup.it - www.vivaldigroup.it
P.IVA e C.F. 02880360272

VIVALDI

